

High Performance Inverter

Communication and I/O Option Cards Available



HP	Three Phase 230VAC (FLA) Variable Torque Fans, Pumps 120% OL - 60 sec	Three Phase 230VAC (FLA) Constant Torque Conveyors, Winding 150% OL - 60 sec	Three Phase 460VAC (FLA) Variable Torque Fans, Pumps 120% OL - 60 sec	Three Phase 460VAC (FLA) Constant Torque Conveyors, Winding 150% OL - 60 sec
1/8 HP		FRN0001E2S-2G (0.8A)		
1/4 HP	FRN0001E2S-2G (1.3A)	FRN0002E2S-2G (1.6A)		
1/2 HP	FRN0002E2S-2G (2.0A)	FRN0004E2S-2G (3.0A)		FRN0002E2S-4G (1.5A)
1	FRN0004E2S-2G (3.5A)	FRN0006E2S-2G (5.0A)	FRN0002E2S-4G (1.8A)	FRN0004E2S-4G (2.5A)
1.5	FRN0006E2S-2G (6.0A)		FRN0004E2S-4G (3.4A)	
2		FRN0010E2S-2G (8.0A)		FRN0006E2S-4G (4.2A)
3	FRN0010E2S-2G (9.6A)	FRN0012E2S-2G (11A)	FRN0006E2S-4G (5.0A)	FRN0007E2S-4G (5.5A)
4	FRN0012E2S-2G (12A)		FRN0007E2S-4G (6.3A)	
5		FRN0020E2S-2G (17.5A)		FRN0012E2S-4G (9.0A)
7.5	FRN0020E2S-2G (19.6A)	FRN0030E2S-2G (25A)	FRN0012E2S-4G (11.1A)	FRN0022E2S-4G (13A)
10	FRN0030E2S-2G (30A)	FRN0040E2S-2G (33A)	FRN0022E2S-4G (17.5A)	FRN0029E2S-4G (18A)
15	FRN0040E2S-2G (40A)	FRN0056E2S-2G (47A)	FRN0029E2S-4G (23A)	FRN0037E2S-4G (24A)
20	FRN0056E2S-2G (56A)	FRN0069E2S-2G (80A)	FRN0037E2S-4G (31A)	FRN0044E2S-4G (30A)
25	FRN0069E2S-2G (69A)	FRN0088E2S-2G (76A)	FRN0044E2S-4G (38A)	FRN0059E2S-4G (39A)
30	FRN0088E2S-2G (88A)	FRN0115E2S-2G (90A)	FRN0059E2S-4G (45A)	FRN0072E2S-4G (45A)
40	FRN0115E2S-2G (115A)		FRN0072E2S-4G (60A)	FRN0085E2S-4G (60A)
50			FRN0085E2S-4G (75A)	FRN0105E2S-4G (75A)
60			FRN0105E2S-4G (91A)	FRN0139E2S-4G (91A)
75			FRN0139E2S-4G (112A)	FRN0168E2S-4G (112A)
100			FRN0168E2S-4G (150A)	FRN0203E2S-4G (150A)
125			FRN0203E2S-4G (176A)	FRN0240E2S-4G (176A)
150			FRN0240E2S-4G (210A)	FRN0290E2S-4G (210A)
200			FRN0290E2S-4G (253A)	FRN0361E2S-4G (253A)
250			FRN0361E2S-4G (304A)	FRN0415E2S-4G (304A)
300			FRN0415E2S-4G (377A)	FRN0520E2S-4G (377A)
350			FRN0520E2S-4G (415A)	FRN0590E2S-4G (415A)
400				
450			FRN0590E2S-4G (520A)	